TIRA Schwingtechnik
Vibration Test Systems

Digital Amplifier A 3 08 11 042

TECHNICAL PARAMETERS Amplifier A 3 08 11 042

Max. ouput power$_{RMS}$	25 kVA
Frequency range	DC - 5000 Hz
Voltage$_{RMS}$, max.	212 V
Current$_{RMS}$, max.	200 A
Signal input voltage$_{PK}$	±10 V
Total Harmonic Distortion (at 70A$_{RMS}$, 200 Hz)	< 0.2 %
Signal to noise ratio	> 85 dB
Field power suppy	internal
Field voltage	105 V
Field current	75 A
Total mass	650 kg
Dimensions (WxHxD)	600 x 2200 x 800 mm
Power supply	3~ / N / PE 400 V±5% 50 Hz, CEE 63
Recommended fuse protection	50 A slow
Max. power consumption at 400 V (at operation with vibration test system TV 59327)	30 kVA
Interlocks:	Overload, Temperature, Displacement, Cooling air, Compressed air, Phase monitoring, Emergency stop



Features:
- TIRA Digital amplifiers can be adapted to almost all shakers existing on the market
- Low distortion factor of up to < 0.2 %
- High clock frequency power modules of 102 kHz ±5%
- Multifunctional LC-touch screen display
- Error indication and system parameters are shown in plain text
- Safety management monitors temperature, overcurrent, overtravel and air supply of the vibration test system
- Inputs for additional safety functions from external sources
- Adjustable current limit
- Adjustable output voltage offset
- Field power supply integrated
- Integrated mains switch and line filter
- Field voltage/current variable according to customer specification
- 4 Sigma peak current
- Lo-Field/Hi-Field (Energy-saving mode)
- Power cable length 10 m (Standard) with CEE 63 connector (variable according to customer specification)

TIRA GmbH Eisfelder Str. 23/25, 96528 Schalkau, Germany • Phone: +49 36766 280-0 • Fax: +49 36766 280-99 • Internet: www.tira-gmbh.de • Email: st@tira-gmbh.de

© TIRA GmbH • Version 05 - 2026-03-05

Subject to modifications